


































































































































Feature Matrix for FortiSwitchOS 7.4.1

The following table lists the FortiSwitch features in Release 7.4.1 that are supported on each series of FortiSwitch models. All features are available in Release 7.4.1, unless otherwise stated. Features marked with ✓ are supported by FortiSwitch units in standalone mode; features marked with  are supported in both standalone and in managed mode. Security Fabric features are available exclusively in managed mode when supported by the FortiOS version.

Feature	GUI Supported	FSR-112D-POE	FSR-124D	FSR-424F-POE	1xxE, 1xxF	200 Series	4xxE	500 Series	1024D, 1024E, 1048E, T1024E	3032E
Security Fabric (exclusively in managed mode)										
Centralized configuration										
Centralized firmware management										
Automated detection and recommendations										
Syslog collection	—									
Device detection										
Network device detection	—	—			—					
Block intra-VLAN traffic (See Note 7.)										
Host quarantine										
Integrated FortiGate network access control (NAC) function										
NAC LAN segments (See Note 12.)										
FortiGuard IoT identification										
Support of matching FortiClient EMS tags in NAC policies										
Support of matching IoT/OT vulnerabilities in NAC policies										

Feature	GUI Supported	FSR-112D-POE	FSR-124D	FSR-424F-POE	1xxE, 1xxF	200 Series	4xxE	500 Series	1024D, 1024E, 1048E, T1024E	3032E
Dynamic port policies										
FortiSwitch VLANs over VXLAN	—	—	—	—	—	—	—	—	 (1024E, 1048E, T1024E)	
FortiLink management over VXLAN	—	—	—		—	—				
FortiView Internal Hubs		—			—					
NAC device telemetry	—	—			—					
Inter-VLAN routing offload	—	—	—	—	—	—	—	—		
FortiLink Secure Fabric Authentication	—									
FortiLink Secure Fabric Encryption	—									
Management and Configuration										
CPLD software upgrade support for OS	—	—	—	—	—	—	—	—	1024D	—
Firmware image rotation (dual-firmware image support)	—	✓	✓	✓	124F, 124F-POE, 124F-FPOE, 148E, 148E-POE, 148F, 148F-POE, 148F-FPOE	✓	✓	✓	✓	✓
HTTP REST APIs for configuration and monitoring	—	✓	✓	✓	✓	✓	✓	✓	✓	✓
Support for switch SNMP OID										
IP conflict detection and notification	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
FortiLAN Cloud configuration	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
FortiSwitch Manager configuration	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
Auto topology	—									
Security and Visibility										

Feature	GUI Supported	FSR-112D-POE	FSR-124D	FSR-424F-POE	1xxE, 1xxF	200 Series	4xxE	500 Series	1024D, 1024E, 1048E, T1024E	3032E
RADIUS for administrative authentication	—	✓	✓	✓	✓	✓	✓	✓	✓	✓
TACACS+ for administrative authentication	—	✓	✓	✓	✓	✓	✓	✓	✓	✓
802.1X port mode	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
802.1X MAC-based mode	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
802.1X MAC-based mode: Wake-on-LAN	—	✓	✓	✓	✓	✓	✓	✓	✓	✓
User-based (802.1X) VLAN assignment	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
802.1X: MAB	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
802.1X MAB entry aging										
open-auth mode	✓	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
MAC move	—	—	✓	✓	✓	✓	✓	✓	✓	✓
802.1X/MAB priority	—	✓	✓	✓	✓	✓	✓	✓	✓	✓
Support of the RADIUS accounting server	Partial	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
Support of RADIUS CoA and disconnect messages	—	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
EAP pass-through	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
IP-MAC binding (IPv4)	✓	—	—	—	—	—	—	🔗	🔗	🔗
sFlow (IPv4)	✓	🔗	🔗	🔗	🔗 (124F, 148E, 148F)	🔗	🔗	🔗	🔗	🔗
Flow export (IPv4)	✓	—	🔗	🔗	🔗 (124F, 148F)	🔗	🔗	🔗	🔗	🔗
ACL (IPv4) (See Note 17.)	✓	🔗	🔗	🔗	✓	🔗	🔗	🔗	🔗	🔗
ACL (IPv6 ingress)	—	—	—	✓	—	✓	✓	✓	✓	✓
Multistage ACL (IPv4)	✓	—	—	—	—	—	—	✓	✓	✓
Multiple ingress ACLs (IPv4)	✓	—	✓	✓	—	✓	✓	✓	✓	✓

Feature	GUI Supported	FSR-112D-POE	FSR-124D	FSR-424F-POE	1xxE, 1xxF	200 Series	4xxE	500 Series	1024D, 1024E, 1048E, T1024E	3032E
Schedule for ACLs (IPv4)	—	—	✓	✓	✓	✓	✓	✓	✓	✓
Dynamic ACLs (IPv4)	—	—	✓	✓	✓	✓	✓	✓	✓	✓
ACL: color marking (IPv4)	✓	—	—	✓	—	✓	✓	✓	✓	✓
DHCP snooping (See Note 16.)	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
DHCPv6 snooping	✓	—	—	✓	—	✓	✓	✓	✓	✓
DHCP-snooping static entries (IPv4)	—	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
DHCP-snooping option 82	—	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
Allowed DHCP server list	✓	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
Flap guard	—	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
IP source guard (IPv4)	✓	—	🔗	🔗	—	🔗	🔗	—	—	—
IP source-guard violation log	—	—	✓	✓	—	✓	✓	—	—	—
Dynamic ARP inspection (IPv4)	✓	—	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
ARP timeout value	—	✓	✓	✓	✓	✓	✓	✓	✓	✓
RMON group 1	—	✓	✓	✓	✓	✓	✓	✓	✓	✓
Reliable syslog	—	✓	✓	✓	✓	✓	✓	✓	✓	✓
Packet capture	🔗	—	🔗	🔗	🔗 (124F, 148E, 148F)	🔗	🔗	🔗	🔗	🔗
MACsec: PSK mode (See Note 6.)	✓	—	—	—		—	—	🔗	🔗 (1024E, T1024E)	—
MACsec: Dynamic-CAK mode (See Note 6.)	✓	—	—	—		—	—	🔗	🔗 (1024E, T1024E)	—

Feature	GUI Supported	FSR-112D-POE	FSR-124D	FSR-424F-POE	1xxE, 1xxF	200 Series	4xxE	500 Series	1024D, 1024E, 1048E, T1024E	3032E
Learning-limit violation action	—	✓	✓	✓	✓	✓	✓	✓	—	—
set mac-violation-timer	—	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
Sticky MAC	✓	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
Warning when the layer-2 table is getting full	—	—	✓	✓	—	✓	✓	✓	—	—
MSTP instances	—	0-15	0-15	0-15	0-15	0-15	0-15	0-32	0-32	0-32
STP root guard	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
STP BPDU guard	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
Rapid PVST interoperation	—	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
'forced-untagged' or 'force-tagged' setting on switch interfaces	—	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
Private VLANs	✓	—	✓	✓	—	✓	✓	✓	✓	✓
Multi-stage load balancing	—	—	—	—	—	—	—	—	✓	✓
Priority-based flow control	—	—	—	—	—	—	—	✓	✓	✓
Ingress pause metering	—	—	—	🔗	—	🔗	🔗	🔗	🔗 (1024D, 1048E)	—
Storm control	✓	🔗	🔗	🔗	🔗	🔗	🔗	🔗		🔗
Per-port storm control	✓	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
Global burst-size control	✓	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
MAC/IP/protocol-based VLAN assignment	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
Virtual wire	✓	—	✓	✓	—	✓	✓	✓	✓	✓
Loop guard	✓	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
Percentage rate control	🔗	—	🔗	🔗	—	🔗	🔗	🔗	🔗	🔗
VLAN stacking (QnQ)	✓	—	✓	✓	—	✓	✓	✓	✓	✓

Feature	GUI Supported	FSR-112D-POE	FSR-124D	FSR-424F-POE	1xxE, 1xxF	200 Series	4xxE	500 Series	1024D, 1024E, 1048E, T1024E	3032E
VLAN mapping (See Note 13.)	✓	✓	✓	✓	124F, 124F-POE, 124F-FPOE, 148F, 148F-POE, 148F-FPOE	✓	✓	✓	✓	✓
SPAN	✓	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
RSPAN and ERSPAN (IPv4)	✓	🔗 (RSPAN)	🔗	🔗	—	🔗	🔗	🔗	🔗	🔗
FortiOS one-arm sniffer	—	🔗 (RSPAN)	🔗	🔗	—	🔗	🔗	🔗	🔗	🔗
Traffic policy (policer)	—	—	🔗	🔗	—	🔗	🔗	🔗	🔗	🔗
Flow control	—	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
MRP	—	✓	✓	—	—	—	—	—	—	—
Layer 3										
VXLAN (See Note 15.)	—	—	—	—	—	—	—	—	✓ (1024E, 1048E, T1024E)	✓
VXLAN: STP virtual root	—	—	—	✓	—	—	✓	✓	✓ (1024E, 1048E, T1024E)	—
VXLAN: BGP EVPN	—	—	—	—	—	—	—	—	✓ (1024E, 1048E, T1024E)	✓
VXLAN: Duplicate address detection	—	—	—	—	—	—	—	—	✓ (1024E, 1048E, T1024E)	✓
VXLAN: ARP/ND suppresion	—	—	—	—	—	—	—	—	✓ (1024E, 1048E, T1024E)	✓
VXLAN: ECMP	—	—	—	—	—	—	—	—	✓ (1024E, 1048E, T1024E)	✓
RVI	—	—	—	✓	—	—	448E, 448E-FPOE, 448E-POE, 424E-Fiber	✓	✓	✓

Feature	GUI Supported	FSR-112D-POE	FSR-124D	FSR-424F-POE	1xxE, 1xxF	200 Series	4xxE	500 Series	1024D, 1024E, 1048E, T1024E	3032E
Link monitor (IPv4/IPv6)	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
Static routing (IPv4/IPv6) (See Note 9.)	✓	—	✓	✓	✓	✓	✓	✓	✓	✓
Software-based routing only (IPv4/IPv6)	✓	✓	—	—	✓	—	—	—	—	—
Hardware-based routing (IPv4/IPv6)	✓	—	✓	✓	—	✓	✓	✓	✓	✓
ECMP with hardware-based routing (IPv4/IPv6)	—	—	—	—	—	—	—	✓	✓	✓
Static BFD (IPv4/IPv6)	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
uRPF	—	—	—	—	—	—	—	✓	✓	✓
DHCP relay (IPv4)	✓	—	✓	✓	✓	✓	✓	✓	✓	✓
DHCP server (IPv4)	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
Layer 3: Requires Advanced Features License										
Policy-based routing (IPv4)	✓	—	—	✓	—	✓	✓	✓	✓	✓
VRF (IPv4/IPv6)	✓	—	—	—	—	—	—	✓	✓	✓
OSPF (IPv4/IPv6)	✓	—	—	✓	—	✓	✓	✓	✓	✓
BFD for OSPF (IPv4/IPv6)	✓	—	—	✓	—	✓	✓	✓	✓	✓
OSPF database overflow protection (IPv4)	—	—	—	✓	—	✓	✓	✓	✓	✓
OSPF graceful restart (IPv4, helper mode only)	—	—	—	✓	—	✓	✓	✓	✓	✓
OSPF: VRF support (IPv4)	✓	—	—	—	—	—	—	✓	✓	✓
RIP (IPv4/IPv6)	✓	—	—	✓	—	✓	✓	✓	✓	✓
BFD for RIP (IPv4/IPv6)	—	—	—	✓	—	✓	✓	✓	✓	✓
VRRP (IPv4/IPv6)	✓	—	—	✓	—	✓	✓	✓	✓	✓
BGP (IPv4/IPv6)	—	—	—	✓	—	—	✓	✓	✓	✓
BFD for BGP (IPv4/IPv6)	—	—	—	✓	—	—	✓	✓	✓	✓

Feature	GUI Supported	FSR-112D-POE	FSR-124D	FSR-424F-POE	1xxE, 1xxF	200 Series	4xxE	500 Series	1024D, 1024E, 1048E, T1024E	3032E
IS-IS (IPv4/IPv6)	✓	—	—	✓	—	✓	✓	✓	✓	✓
BFD for IS-IS (IPv4/IPv6)	—	—	—	✓	—	✓	✓	✓	✓	✓
PIM (IPv4)	✓	—	—	—	—	—	✓	✓	✓	✓
High Availability										
MCLAG (multichassis link aggregation)	Partial	—	—	🔗	—	🔗	🔗	🔗	🔗	🔗
STP supported in MLAGs	—	—	—	🔗	—	🔗	🔗	🔗	🔗	🔗
IGMP snooping support in MCLAG	✓	—	—	🔗	—	🔗	🔗	🔗	🔗	🔗
Layer-3 (IPv4) routing in MCLAG	—	—	—	VRRP and static	—	VRRP and static	VRRP and static	✓	✓	✓
High-Availability Seamless Redundancy (HSR)	—	—	—	✓	—	—	—	—	—	—
Parallel Redundancy Protocol (PRP)	—	—	—	✓	—	—	—	—	—	—
Quality of Service										
802.1p support, including priority queuing trunk and WRED (See Note 19.)	✓	—	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
QoS queue counters	—	—	🔗	🔗	—	🔗	🔗	🔗	🔗	🔗
Tail-drop policy	✓	—	✓	✓	✓	✓	✓	✓	✓	✓
RED drop policy	✓	—	✓	—	—	✓	—	—	—	—
WRED drop policy	✓	—	—	✓	—	—	✓	✓	✓	✓
Egress drop mode	—	—	—	—	—	—	—	✓	✓	✓
QoS marking (IPv4/IPv6)	—	—	✓	✓	—	✓	✓	✓	✓	✓
Summary of configured queue mappings	🔗	—	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
Egress priority tagging (IPv4/IPv6)	—	—	🔗	🔗	—	🔗	🔗	🔗	🔗	🔗
ECN (IPv4/IPv6)	✓	—	—	🔗	—	—	🔗	🔗	🔗	🔗

Feature	GUI Supported	FSR-112D-POE	FSR-124D	FSR-424F-POE	1xxE, 1xxF	200 Series	4xxE	500 Series	1024D, 1024E, 1048E, T1024E	3032E
Real-time egress queue rates (See Note 11.)	—	—	—	✓	148F, 148F-POE, 148F-FPOE	✓	✓	✓	✓	✓
Miscellaneous										
PoE-pre-standard detection (See Note 1.)	—	🔗	🔗	🔗	🔗 (1xxE-POE)	🔗	🔗	🔗	—	—
PoE modes support: first come, first served or priority based (PoE models)	—	🔗	🔗	🔗	🔗 (1xxE-POE)	🔗	🔗	🔗	—	—
Perpetual PoE (See Notes 1 and 14.)	—	—	—	✓	🔗	—	—	—	—	—
PoE disconnection type	—	—	—	✓	—	✓	✓	—	—	—
Split port (See Note 5.)	Partial	—	—	—	—	—	—	🔗	🔗 (1024E, 1048E, T1024E)	🔗
TDR (time-domain reflectometer)/cable diagnostics support	🔗	—	🔗	🔗	🔗	🔗	🔗	🔗	—	—
Auto module max speed detection and notification	✓	—	—	—	—	—	—	✓	✓	—
Monitor system temperature (threshold configuration and SNMP trap support) (See Note 10.)	—	✓	✓	✓	✓	✓	✓	✓	✓	✓
MAC notification SNMP trap	—	✓	✓	✓	✓	✓	✓	✓	✓	✓
Cut-through switching	—	—	—	—	—	—	—	—	1024D	✓
Add CLI to show the details of port statistics	—	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
Configuration of the QSFP low-power mode	—	—	—	—	—	—	—	✓	1024E, 1048E, T1024E	✓
Energy-efficient Ethernet	✓	✓	✓	✓	✓	✓	✓	✓	—	—
PHY Forward Error Correction (See Note 4.)	—	—	—	—	—	—	—	—	1024E, 1048E, T1024E	✓
PTP version 2 transparent clock (IPv4/IPv6) (See Note 8.)	—	—	—	🔗	—	🔗	🔗	🔗	🔗 (1024E, 1048E, T1024E)	🔗

Feature	GUI Supported	FSR-112D-POE	FSR-124D	FSR-424F-POE	1xxE, 1xxF	200 Series	4xxE	500 Series	1024D, 1024E, 1048E, T1024E	3032E
Alias commands	—	✓	✓	✓	✓	✓	✓	✓	✓	✓
Automation stitches	—	✓	✓	✓	✓	✓	✓	✓	✓	✓
Multiple path traceroute	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
Wake-on-LAN packets	—	✓	✓	✓	✓	✓	✓	✓	✓	✓
Save event log in flash memory	—	—	✓	✓	—	✓	✓	✓	✓	✓

Notes

- PoE features are applicable only to the model numbers with a POE or FPOE suffix.
- The 24-port LAG is applicable to FS-524D, FS-524-FPOE, FS-1024D, and FS-3032D models. The 48-port LAG is applicable to FS-548D, FS-548-FPOE, and FS-1048D models.
- The per-VLAN MAC learning limit is not supported on the FS-108E, FS-108E-POE, FS-108E-FPOE, FS-108F, FS-108F-POE, FS-108F-FPOE, FS-124E, FS-124E-POE, FS-124E-FPOE, FS-124F, FS-124F-POE, FS-124F-FPOE, FS-448D, FS-448D-POE, FS-448D-FPOE, FS-248E-POE, FS-248E-FPOE, and FS-248D models. The per-trunk MAC learning limit is not supported on the FS-448D, FS-448D-POE, FS-448D-FPOE, FS-248E-POE, FS-248E-FPOE, and FS-248D models.
- Supported only in 100G mode (clause 91).
- On the FS-3032E, you can split one port at the full base speed, split one port into four sub-ports of 25-Gbps each (100G QSFP only), or split one port into four sub-ports of 10-Gbps each (40G or 100G QSFP).
- Supported on the 10G ports on the FS-5xxD models, the 10G and 100G ports on the FS-1024E model, and the 100G ports on the FS-T1024E model.
- The maximum number of access VLANs on the FS-1xxE, FS-108F, FS-108F-POE, and FS-108F-FPOE models is 16; the maximum number of access VLANs on the FS-148F models is 32.
- PTP is not supported on the FS-248E, FS-248E-POE, FS-248E-FPOE, FS-448D, FS-448D-POE, and FS-448D-FPOE models. The FSR-424F-POE model supports PTP transparent clock with IPv4 addresses only.
- In managed mode, static routing is supported exclusively for system management and connectivity to Security Fabric connectors.
- This feature is not supported by the FS-108E, FS-108E-POE, FS-108E-FPOE, FS-108F, FS-108F-POE, FS-108F-FPOE, FS-124E, FS-124F, and FS-224E models.
- The FS-148F, FS-148F-POE, and FS-148F-FPOE models report the drop rate as 0 or +VE for a positive rate.
- There are some limitations on LAN segments on the FSR-112D-POE, FS-108E, FS-108E-POE, FS-108E-FPOE, FS-108F, FS-108F-POE, FS-108F-FPOE, FS-124E, FS-124E-POE, FS-124E-FPOE, FS-148E, and FS-148E-POE models. See the *FortiLink Guide—FortiSwitch Devices Managed by FortiOS 7.2* for details.
- Partial VLAN mapping is supported by the FS-124F, FS-124F-POE, FS-124F-FPOE, FS-148F, FS-148F-POE, FS-148F-FPOE, and FSR-112D-POE models. See the *FortiSwitchOS Administration Guide 7.2.0* for details.
- When the FortiSwitch unit is using `poe-port-power perpetual-fast`, the following BIOS versions are required: 4000014 or higher for FS-108E-POE, FS-108E-FPOE, FS-124E-POE, and FS-124E-FPOE; 4000011 or higher for FS-148E-POE; 4000006 or higher for FS-108F-FPOE; and 4000007 or higher for FS-108F-POE.
- The FS-3032E model does not support multiple next hops on the same port.

16. The 1xx models allow you to enable DHCP snooping on a maximum of 25 VLANs.

17. Only the ACL ingress policy is supported in FortiLink mode. The following FortiSwitch models do not support ACL in FortiLink mode: FS-108E, FS-108E-POE, FS-108E-FPOE, FS-108F, FS-108F-POE, FS-108F-FPOE, FS-124E, FS-124E-POE, FS-124E-FPOE, FS-124F, FS-124F-POE, FS-124F-FPOE, FS-148E, FS-148E-POE, FS-148F, FS-148F-POE, FS-148F-FPOE, and FSR-112D-POE.

18. OS image signature verification is not supported on the FS-224D-FPOE and FS-248D models.

19. The FS-1xxE and FS-1xxF models support a single QoS map. If there is more than one QoS map, the first configured map is used.

Copyright© 2023 Fortinet, Inc. All rights reserved. Fortinet®, FortiGate®, FortiCare® and FortiGuard®, and certain other marks are registered trademarks of Fortinet, Inc., in the U.S. and other jurisdictions, and other Fortinet names herein may also be registered and/or common law trademarks of Fortinet. All other product or company names may be trademarks of their respective owners. Performance and other metrics contained herein were attained in internal lab tests under ideal conditions, and actual performance and other results may vary. Network variables, different network environments and other conditions may affect performance results. Nothing herein represents any binding commitment by Fortinet, and Fortinet disclaims all warranties, whether express or implied, except to the extent Fortinet enters a binding written contract, signed by Fortinet's General Counsel, with a purchaser that expressly warrants that the identified product will perform according to certain expressly-identified performance metrics and, in such event, only the specific performance metrics expressly identified in such binding written contract shall be binding on Fortinet. For absolute clarity, any such warranty will be limited to performance in the same ideal conditions as in Fortinet's internal lab tests. In no event does Fortinet make any commitment related to future deliverables, features, or development, and circumstances may change such that any forward-looking statements herein are not accurate. Fortinet disclaims in full any covenants, representations, and guarantees pursuant hereto, whether express or implied. Fortinet reserves the right to change, modify, transfer, or otherwise revise this publication without notice, and the most current version of the publication shall be applicable.